

REDRAGON

ARROW PRO CARBON

ARROW PRO CARBON 4-MODES GAMING HEADSET

Please scan here to download user manual

Arrow Pro Carbon 4-modes gaming headset Operating Instructions

US UK

Dear user

Thank you for choosing our REDRAGON product. To protect your rights and for better customer service, we ask that you note our warranty rules.

1. Within guaranty period, repair is guaranteed for failure due to electrical circuit problems. Other damages, such as disassembly, hard impacts, submersion into water, plugging into improper current or voltage, and damage caused by natural disasters such as fire, flood, or earthquake are not included.

2. Consumable parts (such as foot pad) and spare parts replacement are not included in our warranty.

OS Support

Windows XP/Vista/Win7/Win8/Win10/Win11/Switch/PS3/4/5/Xbos one

Packaging content:

A. Headset -----1 unit

B. USB dongle -----1 unit

C. TYPE C charging cable-----1 unit

D. Type C switch to 3.5mm cable -----1 unit

1

Headset button and receiver LED indication:

Receiver LED:
①Blue LED twinkle : Connecting cut off
②Blue LED light on : Connected, MIC ON
③Blue LED OFF : Connected, MIC mute

Headset button:
①Indicator LED
②Power
③MIC ON/OFF
④Volume button
⑤2.4G/BT switch button
⑥7.1 button
⑦TYPE C charging port

Detachable Microphone

The headset microphone is detachable, please plug it into headset according the fix point, follow the instruction as following photos to plug in.

2

How to charge the headset battery

1) Plug the charging cable to type C slot on headset, plug the charging cable to USB port on PC or DC 5V power adapter, the headset LED turns ON in red while charging, the charging time is around 2.5 hours.

2) Charging at 2.4G/BT mode, the headset will be turns OFF, LED is turn ON in red, LED turns OFF after charging complete.

3) Charging when headset turns OFF, the LED is ON in red, the Red LED will be turn off after charging complete.

Device name

1) USB dongle (USB receiver): H858 Wireless headset

2) Name of USB wired headset device: H858 USB Gaming Headset

3) BT mode headset name : H858

How to pair

1) Plug USB dongle to PC, the dongle LED is on in blue, the blue light is twinkle waiting for pair.

2) When the headphones are turned off in 2.4G mode, press the power button to turn on the headphones, there will be a prompt tone: gaming mode, then long press the 7.1 key for 5 seconds ,there will be a prompt tone: pairing; After successful pairing, there will be a prompt tone: connected. The blue indicator light will remain on;

3) For re-connecting, Headset and dongle will be pairing automatically, dongle LED lights ON in blue.

Headset function instruction

2.4G mode

1) Plug headset dongle to PC/PS4/Smart phone (via Type C port),dongle LED lights ON then twinkle waiting for pairing.

2) Press power button to turn ON headset, start to pairing, headset and dongle LEDs are light on in BLUE after pairing complete. The LEDs are twinkle if pairing failed.

3) Adjust sound volume by volume button.

4) Microphone is default to ON, press MIC button to turn it OFF(Dongle LED turns OFF now), press it again to turn it ON(Dongle LED turns ON now).

5) Headset default to stereo sound effect, press 7.1 button to switch the sound to virtual 7.1 sound effect, headset pump "du du" for indication, do it again switch back to stereo sound(headset pump "du" for indication).

6) Button function in 2.4G as following.

2.4GHz mode

button/function/indicator

Function instruction

How to process

Indication tone

2.4G/BT switch button

Switch 2.4G and BT mode

Click power button

2.4G connecting complete : "Gaming Mode" BT mode connecting complete: "BT mode, Pairing"

Volume + button

Increase volume

Click press and hold

Max volume: "Du Dong"

Volume - button

Decrease volume

Click press and hold

Minimum volume: "Du Dong"

Microphone ON/OFF button

MIC ON/Mute

Click

Mute: "Ding Dong" ON: "Ding" Default: to ON(Dongle LED is ON)

7.1 button

2.0 / 7.1 Sound effect switching

Click

Default to Stereo sound: Du, Click to virtual 7.1 sound: "DuDu"

Power button

ON/OFF

Turn ON : Press and hold for 1.5 second
Turn OFF : Press and hold for 3 seconds

2.4G: Gaming mode Turn off headset: Power off Pairing complete: Connected

Left earcup

4

Headset charging indicator

Headset working indicator

Red light is always on when charging, and off when fully charged

Flashes in blue when not connected, and blue light is always on after connected

Dongle

Dongle indicator

Flashes in blue when not connected, and blue light is always on after connected; when the microphone is turned off, the blue light is off

Wired mode with 3.5mm cable

1) Please take off the dongle if headset works at 2.4G mode, turn OFF the headset.

2) Take out the type C-3.5mm cable, plug to PC 3.5mm audio port of cell phone or notebook, Plug the type C to headset, now the headset is in wired headphone mode . At this time, the headphones are stereo headphones with microphone recording function and no button function.

3) For PC connecting, please find a 1 to 2 adaptor cable to meet the PC 3.5mm port.

BT mode

1) Turn on headset, switch to BT mode, indication tone: "BT mode", headset ready to pairing.

2) Find the Redragon headset device named H858 in the list, then press it to pairing

3) The indication tone: "connected" after pairing successful.

4) This earphone is compatible with most BT phones and other devices that support the BT earphone protocol.

5) Headset default to stereo sound in BT mode, not available with other sound effect.

6) When pairing other phones, please press the microphone button for 3 seconds while in BT mode, and the headphones will enter pairing mode;

7) Button function in BT mode as following;

5

BT mode

Button/function

Function indication

How to process

Indication tone

2.4G/BT switch button

Switch 2.4G and BT mode

Click power button

2.4G connecting complete: "Gaming Mode" BT mode connecting complete: "BT mode, Pairing"

Volume + button

Increase volume

Click

Max volume: "Du Dong"

Volume - button

Decrease volume

Click

Minimum volume: "Du Dong"

7.1 button

Switch Stereo and 7.1 mode

Click

Default Stereo mode. 7.1: Du du Stereo: Du

Microphone button ON/OFF

Microphone button ON/Mute

Click

Default to ON
Minimum volume: "Du Dong"

In bluetooth pairing

Press and hold for 3 seconds

Pomp tone: "Pairing"

Power button

ON/OFF

Turn ON: Press and hold for 1.5 second
Turn OFF: Press and hold for 3 seconds

BT : BT mode

Play/pause

Click

Answer/Hang up

Click

Refused phone

Press and hold for 1.5 second

Left earcup

6

USB wired mode

In headset BT mode power on/off status, 2.4G mode power on/off status, connect USB A end of TYPE C TO USB A adapter cable to the computer USB interface, insert TYPE C end into the TYPE C interface of the headset, and the headset will switch to USB wired mode. The button functions are as follows:

Headset charging indicator

Headset working indicator

Red light is always on when charging, and off when fully charged

Flashes in blue when not connected, and blue light is always on after connected

7

Specifications and parameters of H858 four-mode headset

USB mode

Buttons/ functions/lights

Functional description

Operation method

Prompt tone/voice

2.4G/BT switch button

In USB mode, BT/ 2.4G mode cannot be switched online, and the charging cable must be removed to switch modes

Press once

2.4G mode prompt tone: Gaming Mode, BT mode prompt tone: BT mode, Pairing

Vol+ button

Turn up volume

Press once
Press and hold

Maximum volume prompt tone is a beep

Next track

Press twice

Vol- button

Turn down volume

Press once
Press and hold

Minimum volume prompt tone is a beep

Previous track

Press twice

7.1 button

2.0/7.1 sound effect switch

Press once

Default 2.0 mode, press to beep twice to enter 7.1 mode; beep once to enter 2.0 mode

Microphone on/ off button

Microphone on/ mute

Press once

Default is on
Dingdong sound when turning off, Ding when turning on

Power button

Play/pause music

Press once

Headset charging indicator

Headset working indicator

Red light is always on when charging, and off when fully charged

Blue light turns on and flashes in when the headset is turned on, and turns off after when charging

Button description

8

The headset compatibility :

H858 works with following devices

Available devices

BT

2.4G

Wired at 3.5mm port

Wired USB mode

Android phone

Yes

Supported when C port with OTG function is connected with an adapter (TYPE C TO USB A)

Yes (with type C adapter)

USB mode is supported when C port with OTG function is connected with an adapter

Windows notebook

Yes

Yes (by USB port)

Yes (by USB port)

Yes for USB port

Windows PC

N/A

Yes (by USB port)

Yes (by USB port)

Yes for USB port

Apple notebook

Yes

Yes (with type C adapter)

Yes (with type C adapter)

Yes for USB port (Type C docking station USB)

switch

Yes

Yes (with type C adapter)

Yes (with type C adapter)

Yes for Type c adapter

PS/3

N/A

Yes (by USB port)

Yes (by USB port)

Yes for USB port

PS/4

N/A

Yes (by USB port)

Yes (by USB port)

Yes for USB port

PS/5

N/A

Yes (by USB port)

Yes (by USB port)

Yes for USB port

XBOX one

N/A

N/A

N/A

No

Low power warning

The headset indicator lights up in Red and twinkle when the power is below to 3.3V, the indication tone "Battery low", then USB dongle LED twinkle , the headset turn OFF automatically when the power is below to 3.25V.

9

How to storage

The headset should be keep in the condition of temperature of -5 ~ 35 ℃ , it should be a indoor which it is clean and dry environment , please keep it away the corrosive objects and the fire or head source, please charge the headset every 6 months.

Remark

1. Do not put the headset in humid and wet place.

2. High volume for long period may damage your hearing.

3. Do not put self's strength to pull the cable.

FCC Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help
This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

10

This device complies with Part 15 of the FCC Rules and contains licence-exempt transmitter(s)/ receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation

BATTERY SAFETY GUIDELINES

DO NOT replace the battery with a different model.
DO NOT use this product if the battery shows signs of damage including, but not limited to tearing, deformation, leakage, or the smell of electrolytic material.
DO NOT touch the battery if material is leaking and seek immediate medical attention if any material comes into contact with your skin or eyes.
DO NOT expose the battery to liquid, heat sources, electricity (outside of the product itself), or other non-standard operating condition.
DO NOT remove the battery except for proper disposal and recycling as required by local laws and regulations.
DO NOT impact, bend, alter, dissemble, or otherwise damage the battery as the contents are volatile, hazardous, and can be harmful.

CAUTION

Failing to follow all safety guidelines may result product damage, explosion, fire, and/or electric shock.

Cet appareil contient des émetteurs / récepteurs exemptés de licence conformes aux RSS (RSS) d'Innovation, Sciences et Développement économique Canada. Le fonctionnement est soumis aux deux conditions suivantes : (1) Cet appareil ne doit pas causer d'interférences. (2) Cet appareil doit accepter toutes les interférences, y compris celles susceptibles de provoquer un fonctionnement indésirable de l'appareil.

11

型号

HL-9165-H858 Arrow pro carbon

备注： 尺寸：100*100MM（折页）

名称

英文说明书

材质：80g书写纸

日期

2025-7-5

印刷：单黑双面印刷

页码

1 OF 1

文件编号

绘图

杨园园

审核

香敏琪

核准

版本

A.0

Eastemtimes Tech